

## Quick Start Guide Bluetooth Music Receiver WM-BTMIC32

Compatible with the following models:

- **Volvo C30 year 2006-2012**
- **Volvo C70 year 2005-2013**
- **Volvo S40 year 2004-2012**
- **Volvo S60 year 2004-2019**
- **Volvo S80 year 2006-2016**
- **Volvo V50 year 2004-2012**
- **Volvo V70 year 2007-2016**
- **Volvo XC70 year 2007-2016**
- **Volvo XC90 year 2006-2014**

### Connect the Adapter:

1. Remove the radio (you will find various instructions on the Internet).
2. Before disconnecting the plugs from the radio, make sure that the radio code is available to you, as you may need it for the radio after the power cut.
3. Plug the Bluetooth adapter WM-BTMIC32 between vehicle wiring harness and factory radio.
4. Now connect the black ground cable to the radio housing or directly to a ground cable at the vehicle wiring harness (usually a thick brown cable).  
Without a good ground connection the function of the adapter is not possible.
5. Now connect the red cable (ignition plus +12V) to a switched +12V cable. Since this cable is no longer available behind the radio, the voltage can be taken from the cigarette lighter, the fuse box (terminal 15) or the air conditioner (measurement with multimeter necessary). Ignition on = +12V present / ignition off = 0V present.
6. Place the microphone near the driver in the vehicle (steering wheel cover, dashboard, etc.).  
The cable is then routed to the Bluetooth adapter and connected to the microphone input.  
**Avoid placing the microphone in the direct area of or on airbags.**
7. Establish a Bluetooth connection by enabling Bluetooth pairing and searching for the Bluetooth device ``WM``.  
You should then set the volume on the connected mobile device to maximum.
8. Before reinstalling the radio, test the function of the adapter. Switch on the AUX function via the CD/AUX button or the menu on the radio.

### Attention!

The AUX function must be selectable or activated via the CD or MODE button!

If AUX is not displayed in the menu, the AUX input must be enabled in a workshop, otherwise the adapter will not be detected.

Not compatible with fiber optic cabling!

Anything unclear? You can contact us MO-FR, from 8-17 o'clock  
under the e-mail: [service@watermark-germany.de](mailto:service@watermark-germany.de)